AV Equipment Guide

Greenville County Courthouse

The Layout

Judges' Bench

- 1 split-view monitor for courtroom cameras.
- 1 HDMI input cable for judge's laptop (optional)
- 1 control panel
- 1 monitor for judge's review of attorney HDMI and doc cam inputs
- 1 desktop computer for coordinating WebEx/Zoom virtual hearings

Attorney's Table

- 1 touch panel
- 1 monitor
- 1 document camera
- 1 HDMI input cable with adapters

Jury Box

• 2 TV monitors facing towards the jury

Additional

- 1 witness stand monitor
- 1 TV monitor behind witness stand
- 2 TV monitors located next to each attorney table
- Microphones located throughout the courtroom at the following locations:
 - o Judge
 - o Witness
 - o Attorney Left
 - Attorney Left Wireless
 - o Attorney Right
 - o Attorney Right Wireless
 - o Lectern
- Brand new Wi-Fi for better coverage and strength.
- Brand new wireless lapel microphone system

At the Judge's Bench

Judges will have universal control over the video and audio of the courtroom. They will have the ability to mute specific microphones, mute all microphones, turn off or on specific monitors, control what is shown on the monitors, and many other features.

Main Control Page

This is the first screen that appears on the judge's control panel when the system is booted up. Here you can find all the available options. The first option that is selected when on the main page is the Presentation Sources.



Presentation Sources

This option allows for judges to control video sources to display and the volume.

On the left side of the screen, there is the "VTC Rx" buttons which controls the video conferencing volume.



On the right side of the screen, there is the "Program" buttons which controls the room program volume.



To Move between Monitors to Display

When an attorney sends a request to present documents to the court, the judge will first receive a preview of the document before it's presented.

When approved, the judge has to select the input source on the screen (Attorney left/right doc cam or Attorney left/right HDMI) followed by the destination.

If the judge only wants to choose certain screens to show the document to, refer to next section labeled "Room Control".

Room Control

Room Control allows for judges to turn on and off certain screens throughout the room.



Notes:

- You cannot turn off all of the displays and just turn on the one(s) you need, as you need them. Turning off all of the displays will cause the system to reboot. Most monitors can be turned off at the display.
- The Jury Displays are referenced from the perspective of the jury and not the judge.

Microphone Control

The judge has the ability to control the volume of the microphones throughout the courtroom. This also includes muting the microphones.



Attorney Lock

Judges have the ability to lock down the attorney's touch panels by selecting the **Lock Attorney Touch Panels** button. When selected, the text will change to display **Unlock Attorney Touch Panels** with a red frame around the panel.



Enable the Sidebar

This button mutes all microphones and plays a white noise sound in the gallery area. A red frame will appear on the touch panels. When selected the text will change from Enable Sidebar to Disable Sidebar.





Service Controls

The button **Service Controls** allows for two functions. It provides the system information along with *Solutionz* contact information in case of any issues. On the same screen, there is an auto-shutdown time. This can be customized so that the system can shut down by itself at a certain time each day.

Presentation	Attorney Touch	Microphone	Enable	Room	Service	Power		
Sources	Panels	Controls	Sidebar	Controls	Controls	System Off	Prev Pa	
Auto-Shutd	own Time							
	Time C)ff	10:00 PM	sc	DUTIC	NIZ		
			▲ ▼			114L		
Project Name: Greenville County Courtroom 6								
Draigat Nu	mhor: Droi?	Project Number: Proj38444 System Name: Greenville County Courtroom 6						
			ourtroom 6					
System Na Project File	me: Greenv ename: Slot			ounty_Courtro	om6_Test_V	6.2.smw		
System Na Project File Programm	me: Greenv ename: Slot er: DG	ille_County_Co 1:Proj38444_C		ounty_Courtro	om6_Test_V	6.2.smw		
System Na Project File Programme Compile Da Program V	ime: Greenv ename: Slot er: DG ate: 3/31/20 ersion: 6.2	ille_County_Co 1:Proj38444_G 21 6:45 AM	Greenville_Co	ounty_Courtro	om6_Test_V	6.2.smw		
System Na Project File Programme Compile Da Program V Control Sys	me: Greenv ename: Slot er: DG ate: 3/31/20 ersion: 6.2 stem Firmwa	ille_County_Co 1:Proj38444_G 21 6:45 AM are: 1.7000.436	Greenville_Co	ounty_Courtro	om6_Test_V	6.2.smw		
System Na Project File Programme Compile Da Program V Control Sys TP1 Touch	ime: Greenv ename: Slot er: DG ate: 3/31/20 ersion: 6.2	ille_County_Co 1:Proj38444_C 21 6:45 AM are: 1.7000.436 ware:	Greenville_Co	ounty_Courtro	om6_Test_V	6.2.smw		
System Na Project File Programm Compile Da Program V Control Sys TP1 Touch TP2 Touch TP3 Touch	me: Greenv ename: Slot er: DG ate: 3/31/20 ersion: 6.2 stem Firmwa Panel Firm Panel Firm	ille_County_Co 1:Proj38444_C 21 6:45 AM are: 1.7000.436 ware: ware:	Greenville_Co	ounty_Courtro	om6_Test_V	6.2.smw		
System Na Project File Programm Compile Da Program V Control Sys TP1 Touch TP2 Touch TP3 Touch	ime: Greenv ename: Slot er: DG ate: 3/31/20; ersion: 6.2 stem Firmwa Panel Firm Panel Firm	ille_County_Co 1:Proj38444_C 21 6:45 AM are: 1.7000.436 ware: ware:	Greenville_Co	ounty_Courtro	om6_Test_V	6.2.smw		
System Na Project File Programm Compile Di Program V Control Sys TP1 Touch TP2 Touch TP3 Touch DigialMedia	me: Greenv ename: Slot er: DG ate: 3/31/20 ersion: 6.2 stem Firmwa Panel Firm Panel Firm Panel Firm a Firmware:	ille_County_Co 1:Proj38444_C 21 6:45 AM are: 1.7000.436 ware: ware:	Greenville_Cc	ounty_Courtro	om6_Test_V	6.2.smw		

Power Shutdown Off

This is the shutdown option for the courtroom system. When selected, a confirmation will appear. Select yes to shut down.

	Shutdown System
YES	NO
	Please Confirm

At the Attorney's Table

At the attorney's table, there is a monitor, a touch panel, a document camera, an HDMI adapter, and 4 different HDMI adapters.

There are two available options for attorneys to present documents: the document camera or the HDMI option.

Using the Camera Doc (Solution Cam):

To present physical documents, place the document under the Solution Cam. When ready, select **Attorney Left/Right Doc Cam** on the *Crestron* control panel. The judge will receive your request.

Camera Doc – Understanding the Buttons:

Zoom In +ZOOM	Zoom Out -ZOOM	Freeze the image in place FREEZE
Auto Focus On/Off AF/FOCUS	Document Camera Light On/Off	Control Panel Shift On/Off

HDMI Adapters:

4 Adapters are provided at each table to connect to HDMI if your device doesn't have an HDMI port. These are the provided adapters:

- 1x Apple ONLY USB Type-C/ Thunderbolt Adapter
- 1x Apple Lightning Adapter
- 1x DisplayPort Adapter
- 1x Mini DisplayPort Adapter



Present Using HDMI

To present electronic documents, only plug in your device when ready to present. Plug either the HDMI cable into your device directly or if you don't have an HDMI port, choose an adapter to connect the HDMI cable to your device.

When you have the document ready to present, select **Attorney Left/Right HDMI** on the *Crestron* control panel. The judge will receive your request.

Switching from Camera Doc to HDMI (and vice versa)

If you are presenting documents one way and wish to present a different way, you must select the other option on the *Crestron* control panel for the judge to receive the new request.

For instance, if you are presenting electronic documents using the option **Attorney Left/Right HDMI** and wish to present physical documents using the camera doc, you must select **Attorney Left/Right Doc Cam**.

Visual Diagrams

Simplified Diagram of the courtroom






Diagram of Judge's Setup



On the left is the courtroom camera feed display. In the middle is the touch panel. On the far right are two displays, one for document preview and the other for the House PC live feed.

Courtroom Camera Feed

Monitor Layout



CAMERA	VIEW	NOTES
Feed 1:	Attorney Table Left or	Speech activated; switches view of
	Attorney Table Right	attorney tables based on person
		speaking
Feed 2:	Witness Stand	Static camera view of the witness stand
		area
Feed 3:	Judge's Bench or Attorney	Speech activated; switches view of
	Lectern	attorney lectern or Judge's bench based
		on person speaking
Feed 4:	House PC	Allows Judge to display whatever is on
		House PC to the courtroom monitors;
		most useful for WebEx/Zoom hearings

Note: While camera views cannot be directly controlled, muting certain microphone will prevent the speech activated cameras from switching view.