



Motorola Site Trunking Guide

1. If your radios ever display “site trunking”, quickly press the button below the PTT switch, and watch the display for the site name.
2. The site name will need to say “Greenville CO” if it does not, press and hold the same button below the PTT switch until it says “scanning” and then release.
3. Press the same button once more (quick press) and see if the site name now says, “Greenville CO”.
4. Once it says “Greenville CO” push the directional arrow buttons left or right until you see the menu item “site”
5. Press the “site” button and you will get two options “lock” and “unlock”
6. Press the “lock” button
7. Once we are out of “site trunking” go back to the site menu option and depress to “unlock”, this returns you to normal operation.

Kenwood Site Trunking Guide

1. If your radios ever display “site trunking”, utilize the Maintenance mode and press the up/down directional keypad the radio will manually scroll between site control channels.
2. After locating the desired site, press the select button.
3. Enter the site lock button to now lock the radio on the desired site. The screen will now have a white flag located next to the status bar on the top of the radio.
4. The radio will no longer roam between sites and stay on the selected site.
5. Once we are out of “site trunking” you will need to exit the site lock mode through the menu.